




Secondary Electron Detector for R&D

MINI-SED is a scintillator type detector that captures secondary electrons and outputs it as electrical signal. It is mainly used as a detector for SEM.

Features



SEM image at 2000 V
(Cu 400 mesh)

- Current detection range: pA ~ μ A
- Response speed: 5MHz
- It can be used at Ultrahigh vacuum. (Baking up to 150 °C is possible.)
- Compact size

Customized SED



with shutter,
ICF 114



Short type
(length: 50 mm)




Thin type
(diameter: ϕ 10 mm)

Specification

| | | |
|---------------------------|----------------------|-----------------------------------|
| Quantum conversion method | | Scintillator |
| Range of detection | Current amount | 1 pA ~ 1 μ A |
| | Response speed | 5 MHz / -3 dB |
| Maximum gain of PMT | | 2×10^5 |
| Input | to Pre-amplifier | DC \pm 8 V / 30 mA |
| | to PMT | 0 ~ -1.0 kV / 300 μ A |
| | to Scintillator | 0 ~ +8 kV / 10 μ A |
| Output | Voltage | 0 ~ 1 V _{P-P} |
| | Impedance | 75 Ω |
| Condition | Degree of vacuum | $\sim 1 \times 10^{-2}$ Pa |
| | Baking temperature | ~ 150 °C (Except the preamp) |
| Interface | | ICF 70 |
| Configuration | Scintillator | |
| | Light Guide | |
| | Photomultiplier tube | |
| | Pre-amplifier | |


Power supply



Power supply for SED is also on sale.

| Specification | |
|---------------|--|
| Functions | Brightness, Contrast, Filter |
| Input | for Pre-amplifier (voltage) for PMT (voltage) for Scintillator (voltage) |
| Output | Single-ended signalling |

Dimensional drawing (example)



* Custom specifications are available by request.

* Specifications are subjected to change without notice.

APCO Ltd.

522-10, Kitano-machi, Hachioji, Tokyo 192-0906, Japan
URL: <http://www.apco-jp.com> e-mail: info@apco-jp.com

tel : +81-42-646-4466(Rep.)

fax : +81-42-656-1404

2018/5/1 SED ver2.0EN